



**UNIVERSITI PUTRA MALAYSIA**

**MAGNETIC CHARACTERISTICS AND MICROSTRUCTURE  
OF SOME FERRITE ANTENNA AND INDUCTOR CORES  
DOPED WITH Co, Ca, AND Si.**

**LOH PIT MUI**

**FSAS 1996 2**

**MAGNETIC CHARACTERISTICS AND MICROSTRUCTURE  
OF SOME FERRITE ANTENNA AND INDUCTOR CORES  
DOPED WITH Co, Ca, AND Si.**

By

**LOH PIT MUI**

Thesis Presented in Fulfilment of the Requirements for the Degree of Master of  
Science in the Faculty of Science and Environmental Studies,  
University Pertanian Malaysia

March, 1996



## DEDICATIONS

*To my beloved father and mother,*

LOH HIN  
LIM KIM MOI

*To my brother and sisters,*

LOH PIK LAN  
LOH SOON SENG  
LOH PIT KHIM

*To my dearest friend*

LEE BOON KOK

*and the members of Ferrite Group in UPM.*

WITHOUT WHOSE LOVE AND CONTINUED  
SUPPORT THIS THESIS WOULD NOT  
HAVE BEEN POSSIBLE.

## ACKNOWLEDGEMENTS

I would like to express my gratitude to my project supervisory chairman, **Dr. Mansor Bin Hashim** for his invaluable guidance and discussions, and his supervision and patience throughout the course of this research. I would also like to thank Dr. Salleh Bin Harun and Dr. Wan Daud Bin Wan Yusof for their constant support.

I am also very grateful to all my dearest friends for their advice and help in various ways. Financial support from Malaysian Government under the IRPA programme is gratefully acknowledged.

Finally, my dearest thanks to my parents and my brother and sisters for their support, care and patience without which this work would never have succeeded.

## TABLE OF CONTENTS

	Page
ACKNOWLEDGEMENTS -----	ii
LIST OF TABLES -----	vii
LIST OF FIGURES -----	viii
LIST OF PLATES -----	xii
LIST OF SYMBOLS AND ABBREVIATIONS -----	xiii
ABSTRACT -----	xv
ABSTRAK -----	xviii
CHAPTER	
I      GENERAL INTRODUCTION -----	1
Historical Overview -----	2
Problems in Ferrite Application -----	3
Objective and Scope of Study -----	4
II      LITERATURE REVIEW -----	8
Introduction -----	8
The Effect of Calcium and Silicon -----	9



	The Effect of Cobalt -----	10
	Microstructural Aspects -----	11
III	SOME IMPORTANT ASPECTS OF TECHNOLOGICAL FERRITES -----	14
	Introduction -----	14
	Composition of Spinel Ferrites -----	16
	Crystal-Lattice Structure -----	16
	Magnetisation -----	18
	Ferrite Microstructure and Grain Growth -----	21
	Magnetic Parameters -----	25
	Magnetic Spectrum -----	25
	Hysteresis Loop -----	28
	Low Frequency Ferrite Loop Antenna and High-Frequency Inductor -----	29
IV	EXPERIMENTAL METHODS AND MEASUREMENT TECHNIQUES -----	32
	Introduction -----	32
	Outline of Work -----	33
	Choice of Materials -----	35
	Sample Preparation -----	37
	Calculation of Weights and Weighing -----	38
	Mixing -----	39

	Presintering -----	40
	Processing of the Presintered Powder -----	41
	Compact Forming -----	41
	Sintering -----	42
	Experimental Measurement -----	44
	Magnetic Spectrum -----	44
	Resistivity -----	45
	Hysteresis Loop -----	46
	Density -----	47
	Microstructure Analysis -----	47
	Sample Preparation for SEM Observation -----	47
	Grain-Size Measurement -----	48
	X-Ray Diffraction Measurement -----	49
V	RESULTS AND DISCUSSION -----	50
	Introduction -----	50
	Magnetic Properties of MgZn-based Ferrites -----	52
	Effect of Directly Added $\text{Co}^{2+}$ on the Magnetic Properties of MgZn- and NiZn-based Ferrites -----	62
	Effect of Forming Pressure on Microstructure, Magnetic, and Mechanical Properties of MgZn- and NiZn-based Ferrites -----	77
	Microstructural and Mechanical Properties -----	77

	Magnetic Properties -----	84
	Electrical Resistivity -----	93
	Comparison of Results and Some Industrial Data -----	95
VI	CONCLUSION -----	96
	Summary of Main Results -----	96
	Final Remarks -----	98
	BIBLIOGRAPHY -----	100
	APPENDICES	
	A -----	108
	B -----	111
	VITA -----	114



## LIST OF TABLES

Table		Page
1	Four different compositions of MgZn-based ferrites. -----	34
2	Resistivity of ferrites and metallic magnetic materials (after Goldman, 1989). -----	36
3	Chemical composition of NiZn-based ferrite. -----	38
4	Typical values of specification parameters for specimens I, II, and NiZn-based ferrites (Snelling, 1988). -----	54
5	Magnetic properties of MgZn-based ferrites with the composition as shown in Table 1. -----	58
6	Initial permeability of Co-added MgZn- and NiZn-based ferrite toroids at 100 kHz. -----	62
7	Operating frequencies ranges for the MgZn- and NiZn-based ferrite toroids. -----	65
8	The Curie temperature of MgZn- and NiZn-based ferrites. -----	68
9	Relation between $\text{Co}^{2+}$ content and temperature coefficient of initial permeability at 100 kHz, ranged from 30 to 100°C, for MgZn- and NiZn-based ferrites toroids. -----	71
10	Comparisons of some magnetic properties for samples prepared in laboratory and samples from industry. -----	95

## LIST OF FIGURES

Figure		Page
1	Two octants of the spinel unit cell. A ions are on tetrahedral sites and B ions on octahedral sites of the $O^{2-}$ anion packaging. -----	17
2	Transition of spin direction at a $180^\circ$ Bloch wall (domain boundary). -----	20
3	Schematic drawing of polycrystalline specimen with grain growth mechanism. -----	24
4	Curve that shows the relationship between Curie temperature and initial permeability. -----	27
5	Characteristic hysteresis loop for a spinel ferrite material. -----	28
6	Flow diagram for the oxide method of ferrite preparation. -----	37
7	Coil placement on the samples with toroid, bar and rectangular plate. -----	44
8	An example of direction of current passing through a toroidal ferrite sample. -----	45
9	The basic configuration that used to measure $B_s$ , $B_r$ , and $H_c$ for a toroidal sample. -----	46
10	Frequency spectra of inductance and quantity factor of bar-shaped MgZn-based ferrite samples. -----	53
11	Frequency spectra of $\mu_i$ and relative loss factor of toroidal MgZn-based ferrite samples. -----	53

12	Temperature dependence of inductance and quality factor of bar-shaped MgZn-based ferrite samples. -----	56
13	Temperature dependence of initial permeability, measured at 100 kHz, of toroidal MgZn-based ferrite samples. -----	56
14	Influence of SiO <sub>2</sub> and CaO additions on the resistivity, (a) and loss factor, (b) of Mn <sub>0.68</sub> Zn <sub>0.21</sub> Fe <sub>2.11</sub> O <sub>4</sub> at 100 kHz (after Akashi, 1961). -----	57
15	Frequency dependences of inductance and quality factor of bar-shaped MgZn-based ferrite samples. -----	59
16	Frequency dependences of initial permeability and relative loss factor of toroidal MgZn-based ferrite samples. -----	59
17	Frequency dependence of initial permeability for MgZn-based ferrites with directly-added CoO. -----	64
18	Frequency dependence of initial permeability for NiZn-based ferrites with directly-added CoO. -----	64
19	Effect of directly-added CoO on frequency dependence of relative loss factor of MgZn-based ferrite toroids. -----	67
20	Effect of directly-added CoO on frequency dependence of $\mu''$ of NiZn-based ferrite toroids. -----	67
21	Initial permeability, measured at 100 kHz, as a function of temperature for MgZn-based ferrite toroids. -----	69
22	Initial permeability, measured at 100 kHz, as a function of temperature for NiZn-based ferrite toroids. -----	69
23	Crystal anisotropy as a function of temperature for Co <sup>2+</sup> additive contributing a positive value to negatively valued host. The compensation point, T <sub>o</sub> , (A) increases with an increase in Co <sup>2+</sup> for a positive total anisotropy (B) decreases with an increase in Co <sup>2+</sup> for a negative total anisotropy (after Slick, 1980). -----	70
24	Effect of variation in Co <sup>2+</sup> level on the anisotropy compensation. -----	72

25	Variation of coercive force, saturated induction, and remanence with concentration of $\text{Co}^{2+}$ ions for MgZn-based ferrite toroids -	74
26	Variation of coercive force, saturated induction, and remanence with concentration of $\text{Co}^{2+}$ ions for NiZn-based ferrite toroids. --	74
27	The sintered densities in specimens of MgZn-based ferrites vs. pressure. -----	78
28	The sintered densities in specimens of NiZn-based ferrites vs. pressure. -----	78
29	Average grain size of MgZn- and NiZn-based ferrites as a function of pressure. -----	83
30	Effect of the pressure on saturated induction, $B_s$ , and remanence, $B_r$ of toroidal MgZn-based ferrites. -----	85
31	Effect of the pressure on saturated induction, $B_s$ , and remanence, $B_r$ of toroidal NiZn-based ferrites. -----	85
32	Variation of coercive force, $H_c$ of toroidal MgZn-based ferrites with pressure. -----	86
33	Variation of coercive force, $H_c$ of toroidal NiZn-based ferrites with pressure. -----	86
34	Inductance spectra of bar MgZn-based ferrites, sintered at 1100°C, for forming pressures indicated. -----	88
35	Inductance spectra of rectangular plate NiZn-based ferrites, sintered at 1150°C, for forming pressures indicated. -----	88
36	Inductance, $L$ , and initial permeability, $\mu_i$ vs. frequency for MgZn-based ferrites, with 11 MPa of forming pressure, sintered at two different temperatures. -----	89
37	Inductance, $L$ , and initial permeability, $\mu_i$ vs. frequency for NiZn-based ferrites, with 9 MPa of forming pressure, sintered at two different temperatures. -----	89

38	Dependency of relative loss factor of toroidal MgZn-based ferrites sintered at 1100°C with different forming pressures on frequency. -----	91
39	Dependency of relative loss factor of toroidal NiZn-based ferrites sintered at 1150°C with different forming pressures on frequency. -----	91
40	Plot of relative loss factor, $RLF = \tan\delta/\mu_i$ vs. frequency for toroidal MgZn-based ferrites with 11 MPa of forming pressure which sintered at two different temperatures. -----	92
41	Plot of relative loss factor, $RLF = \tan\delta/\mu_i$ vs. frequency for toroidal NiZn-based ferrites with 9 MPa of forming pressure which sintered at two different temperatures. -----	92
42	Variations of resistivity with forming pressures of MgZn- and NiZn-based ferrites which sintered at two different temperatures. -----	94
43	The basic configuration that used to measured $B_s$ , $B_r$ , and $H_c$ for a toroidal sample. -----	108
44	Hysteresis loop. -----	109
45	XRD patterns obtained from MgZn- and NiZn-based ferrites specimens (a) Composition I (b) Composition II (c) Composition III (with wet ball milling) (d) Composition IV (e) Composition III (with vibratory milling) (f) NiZn-based ferrites. -----	113

## LIST OF PLATES

Plate		Page
1	Typical SEM photograph of a ferrite. -----	21
2	Samples with the shapes of toroid, bar, and rectangular plate. -----	43
3	Hyteresis loop of MgZn-based ferrite. -----	73
4	Scanning electron micrographs of MgZn-based ferrites, with 11 MPa of green-compact forming pressure, sintered at two different temperatures for 10 h in air; (A) 1100°C (B) 1200°C. -----	80
5	Scanning electron micrographs of NiZn-based ferrites, with 13 MPa of green-compact forming pressure, sintered at two different temperatures for 16 h in air; (A) 1150°C (B) 1200°C. -----	81

## LIST OF SYMBOLS AND ABBREVIATIONS

$H$	applied field
$\mu_B$	Bohr magneton
$H_c$	coercive force
$A$	cross-sectional area
$T_c$	curie temperature
$\rho$	density
$f$	frequency
$\mu''$	imaginary part of permeability or magnetic loss
$L$	inductance
$B$	induction
$\mu_i$	initial permeability
$D_i$	inner diameter
$l$	length
$\tan\delta$	loss tangent
$\mu_0$	magnetic constant
$H_{max}$	magnetic field for effective saturated induction
$N$	no. of wire turns

$D_o$	outer diameter
PVA	polyvinyl alcohol
Q	quality factor
$\mu'$	real part of permeability
RLF	relative loss factor
$B_r$	remanence
R	resistance
$\sigma$	resistivity
$B_s$	saturated induction
$M_s$	saturation magnetisation
SEM	scanning electron microscopy
T	temperature
$\alpha_L$	temperature coefficient of inductance
$\alpha_w$	temperature coefficient of initial permeability
$T_o$	temperature compensation point
t	thickness
$K_t$	total first anisotropy constant
W	weight
XRD	X-ray diffraction



Abstract of the thesis presented to the Senate of Universiti Pertanian Malaysia in fulfilment of requirements for the degree of Master of Science.

**MAGNETIC CHARACTERISTICS AND MICROSTRUCTURE OF SOME  
FERRITE ANTENNA AND INDUCTOR CORES DOPED WITH Co, Ca, AND  
Si.**

By

**LOH PIT MUI**

March, 1996

Chairman : Dr. Mansor Hashim  
Faculty : Science and Environmental Studies

This work gives accounts of an attempt to produce two types of commercial ferrite material whose magnetic characteristics were to be studied in relation to some additives and the microstructure. Two compositions, MgZn- and NiZn-based ferrites, were prepared by the oxide method and characterised mainly in terms of magnetic properties and microstructure. The former composition was to be used as the material for antenna bars and the latter for high-frequency inductors. The antenna material was shaped into bars and toroids while the inductor material into rectangular plates and toroids. The properties of the two compositions were investigated as functions of the amount of additives (CaO and SiO<sub>2</sub> and CoO). The influence of sintering temperature

and forming pressure on magnetic and mechanical properties and average grain size was also studied. The experimental investigation consists of three parts.

Firstly, various compositions of MgZn-based ferrites were prepared and the properties upgraded by suitable additions of CaO and SiO<sub>2</sub>. The inexpensive raw material powder MgO was used to substitute NiO in a composition of commercial NiZn-based ferrite commonly used for antenna bars. A MgZn-ferrite composition with properties matching the commercial material's properties was successfully obtained.

Secondly, the effect of directly-added CoO to MgZn- and NiZn-based ferrites was studied. The addition of CoO for these two original compositions decreased the initial permeability and minimised the variation of initial permeability with temperature. However, the frequency range and the Curie temperature increased with the increase of CoO content. The variations of the properties as a function of the amount of CoO were discussed in terms of the contribution of Co<sup>2+</sup> ions to magnetocrystalline anisotropy.

Thirdly, intentional changes of microstructure for both original compositions were made by varying the forming pressure and sintering temperature. No significant changes on magnetic and mechanical properties and microstructure were found with the increase of forming pressure. However, the average grain size increased with the

sintering temperature, thus, influencing the magnetic and mechanical properties of the samples. The initial permeability increased linearly with grain size.

Abstrak tesis yang dikemukakan kepada Senat Universiti Pertanian Malaysia bagi memenuhi keperluan Izajah Master Sains.

**CIRI MAGNET DAN MIKROSTRUKTUR BEBERAPA ANTENA DAN  
TERAS INDUKTOR FERIT YANG DIDOPKAN DENGAN Co, Ca, DAN Si.**

oleh

**LOH PIT MUI**

Mac, 1996

Pengerusi : Dr. Mansor Hashim  
Fakulti : Sains dan Pengajian Alam Sekitar

Penyelidikan yang dijalankan bertujuan untuk menghasilkan dua jenis bahan ferit komersil yang mana ciri-ciri pemagnetan dihubungkan dengan beberapa jenis bahan penambah dan mikrostruktur. Dua komposisi ferit, masing-masing berasaskan MgZn dan NiZn telah disediakan dengan menggunakan kaedah pengoksidaan dan penciriannya dilakukan berasaskan kepada ciri-ciri magnet dan mikrostruktur. Komposisi yang pertama digunakan sebagai bahan untuk bar antenna dan komposisi yang kedua untuk induktor berfrekuensi tinggi. Bahan antenna yang dikaji adalah dalam bentuk bar dan toroid, sementara bahan induktor berbentuk plat segiempat dan toroid. Ciri-ciri bagi kedua-dua komposisi telah dikaji berfungsi peratusan bahan penambah (CaO dan SiO<sub>2</sub> serta CoO). Di samping itu, kesan suhu pensinteran dan

kesan tekanan terhadap ciri-ciri pemagnetan dan mekanikal serta purata saiz butiran juga telah dikaji. Penyelidikan terbahagi kepada tiga bahagian.

Pertama, beberapa komposisi ferit berasaskan MgZn telah disediakan dan ciri-ciri magnetnya telah dipertingkatkan dengan penambahan peratusan CaO dan SiO<sub>2</sub> yang sesuai. Bahan mentah yang murah, MgO, telah digunakan untuk menggantikan NiO dalam komposisi komersil ferit berasaskan NiZn yang biasanya digunakan untuk bar antenna. Komposisi ferit MgZn dengan ciri-cirinya selaras dengan ciri-ciri bahan yang komersil telah berjaya diperolehi.

Kedua, kesan penambahan CoO secara langsung ke dalam ferit berasaskan MgZn and NiZn juga telah fahami. Penambahan CoO kepada kedua-dua komposisi asal telah menyebabkan penurunan ketelapan awal. Di samping itu, ia juga telah meminimakan perubahan ketelapan awal dengan pertambahan suhu. Walau bagaimanapun, julat frekuensi telah dilebarkan dan suhu Curie meningkat dengan pertambahan kandungan CoO. Perbezaan ciri-ciri ini telah dibincangkan dengan merujuk kepada sumbangan ion-ion Co<sup>2+</sup> kepada ketakisotropan magnetohablur.

Ketiga, perubahan mikrostruktur telah sengaja dilakukan keatas kedua-dua komposisi yang asal dengan mengubah suhu pensinteran dan tekanan. Walau bagaimanapun tidak didapati perubahan yang bermakna terhadap ciri-ciri magnet dan

mekanik serta mikrostruktur dengan pertambahan tekanan. Namun demikian, purata saiz butiran sampel-sampel bertambah dengan pertambahan suhu pensinteran dan sekaligus mempengaruhi ciri-ciri magnet dan mekanik. Ketelapan awal didapati meningkat secara linear dengan saiz butiran, seperti yang dijangka.

## **CHAPTER I**

### **GENERAL INTRODUCTION**

Oxide ceramics which exhibit ferrimagnetic behaviour play an important role in the electronics industry and are commonly known as ferrites. Ferrites are the mixed metal oxides containing iron oxide as their main component. There are three important classes of commercial ferrites, each one having a specific crystal structure: (1) soft ferrites with the cubic spinel structure such as MgZn and NiZn ferrites; (2) soft ferrites with the garnet structure such as the microwave ferrites, for example, yttrium iron garnet; and (3) hard ferrites with the magnetoplumbite (hexagonal) structure such as Ba and Sr hexaferrites. This work investigates some aspects of the magnetic behaviour and microstructure of some spinel ferrites intended for application as loop antenna cores and high-frequency telecommunication inductor cores.

## Historical Overview

Magnetite or ferrous ferrite, a naturally-occurring ferrite, has been known since more than 2000 years ago (Ishino et al., 1987). However, only after the beginning of 20th century (Hilpert, 1909; Forestier, 1928), it was found that some ferrites composed of ferric oxide and another metal oxide showed ferromagnetic properties and the chemical composition of spinel ferrites was clarified. Soon after this, all of the spinel ferrites being used at the time had been developed based on this research.

In 1930s, the first practical ferrite application was in inductors used in inductance-capacitance filters in frequency division multiplex equipment (Kato et al., 1933; Kawai, 1934; Snoek, 1936 and 1947). The combination of high resistivity and good magnetic properties made these ferrites an excellent core material for these filters operating at 50-450 kHz. The large-scale introduction of the television in the 1950s was a major opportunity for the fledgling ferrite industry (Owens, 1956). Ferrite cores were the material of choice in television sets for the high-voltage transformer and the picture-tube deflection system. In the 1970s, ferrite cores were used widely in telecommunication equipment, main-frame computer memories, recording heads, etc. (Hirota et al., 1980). Since the early 1980s, ferrite cores have been used in high-frequency power supplies (Roess, 1982; Bracke, 1983).



### **Problems in Ferrite Application**

Although it is now some decades since spinel ferrites debuted as an important new category of magnetic materials and have attained great commercial importance, it was not long before full-fledged research and development efforts were underway. Therefore, many difficulties have been found to beset the research works in obtaining desired ferrite products.

The chemical aspects of spinel ferrites such as compositional variability and amounts of impurities have long been studied by various workers (Goldman, 1990; Standley, 1972; Snelling, 1988). It has been reported that the amount of an element present in a ferrite composition may affect not only the intrinsic properties but also the microstructure. Thus, apparently, to produce a good-quality product, a specialised working knowledge of ceramic science is needed for a judicious and scientifically reasoned choice of starting constituents that could yield desired properties. The purity level of the raw materials must also be considered as an important basic condition which influences the desired final performance in terms of all the magnetic and electrical properties of the product. This is because the impurities present in the raw materials may have an effect on the properties of a ferrite (Drofenik et al., 1984).

Preparation of spinel ferrites with optimum properties is considered to be most difficult and complex. The main problems involved are due to the fact that most of the